

# The new range of Emergency Door Release Bought to you by RGL.

## EMERGENCY DOOR RELEASE









**RESETKEY-N** 



(only if you require a replacement cover)

### **SPECIFICATION**

### EDR-N

- · Single pole (EDR-1N)
- 1 x Pole (Positive switching)
- · Double pole (EDR-2N)
- 1 x Pole (Positive switching)
- 1 x Pole (Changeover contact)
- · Triple pole (EDR-3N)
- 1 x Pole (Positive switching)
- 2 x Pole (Changeover contact)
- Includes audible/LED (selectable)
- · 12/24V operation
- · Voltage 12/24 VDC @ 30/45mA
- · Operating temperature: -10C to 55C
- · IP24 Rated
- · Resettable

### **FEATURES**

### EDR-N

- · All one colour
- · Easy clean surface (ideal for hospitality areas)
- · Easy cable entry from sides or rear
- Screw footprint for surface fitting onto standard back box
- · Key reset operation (not replacement glass)
- · Internal use
- $\cdot$  Emergence Door Release permanently lit.
- Changes to red on activation/alarm
- Includes plastic front covers which flip up for operation

### **OTHER PRODUCTS**



MEXT-EBGB

**KPX1000** 



### **DIMENSIONS**

### FDR-N

- ·87x87x60 (mm)
- · 248g (Boxed)
- · 162g (Unboxed)

### ISO 9001

+44 (0)1902 656667

### **CONTENTS**

### FDR-N

- · Emergency Door Release
- · EDR-COVER-N
- · Security Screws
- · Allen Key
- · Mounting Plate
- · 2 RESETKEY-N



1201SM-1



www.rgl.co | info@rgl.co